

Presonus StudioLive 16.4.2 Digital Recording Mixer

- 16 mic/line inputs with high-headroom Class A XMAX™ mic preamplifiers
- 4 subgroups
- Stereo/mono main out
- 6 auxiliary mixes
- 32-in/18-out FireWire digital recording interface (24-bit/44.1 kHz and 48 kHz)
- Studio One Artist Digital Audio Workstation software for Mac® and PC
- Capture™ 1.1 recording software for Mac® and PC
- StudioLive Remote mixer-control software for iPad® available free from Apple App Store
- QMix™ aux-control software for iPhone® and iPod touch® available free from Apple App Store
- Direct recording interface compatible with Logic®, Nuendo, Cubase, Sonar™, Digital Performer™, Ableton™ Live, and more
- 16 channel strips
- Trim control with –20 to +20 dBV line/-15 to +65 dBu mic gain range (80dB!)
- +48V phantom power switch for condenser microphones
- FireWire Input Select
- 100 mm precision faders
- Lighted Solo and Mute buttons
- Access to Fat Channel functions
- 15-LED ladder metering + clip LED
- Analog ¼" insert (rear panel)

- 4 subgroup buses, each with:
 - Solo
 - Mute
 - Access to Fat Channel functions (except high-pass filter and phase reverse)

- 6 aux sends, each with
 - Solo
 - Pre/post-fader send
 - Output-level control
 - Access to Fat Channel functions (except phase reverse)
 - Mix and Mix/Pan Fat Channel metering
 - Available sources: Channels 1-16, FXA Return, FXB Return

- 2 internal effects sends, each with:
 - Mute
 - Pre/post-fader send
 - Output-level control
 - Access to Fat Channel (except phase reverse)
 - Effects-send Select for Fat Channel metering
 - Mix button for aux-bus mixing and Fat Channel metering

- Master Section
 - Aux Input A and B
 - Level Control and Select (Fat Channel metering) switch
 - Access to all Fat Channel functions (except phase reverse)

- Talkback System
 - Mic Level control
 - Output Select (Aux 1-2, 3-4, 5-6, Main)
 - Talk button
 - Rear-panel XLR mic input with level control and continuous 48V phantom power

- 2 Track In
 - Level control
 - Tape Input to Mains button
 - FireWire source on/off
- Solo Bus
 - Cue Mix volume control
 - PFL/AFL and Solo In Place (SIP) buttons
- Monitor Bus
 - Headphone-output level control
 - Control-room monitor-level control
 - Solo Bus to Monitor button
 - Tape Input to Monitor button
 - Main L/R FireWire Return to Monitor button
 - Main Mix to Monitor button
- Fat Channel with rotary encoders:
 - Pan with dedicated 15-LED display
 - Stereo link for input channels, aux buses, and subgroups
 - Phase reverse (main channels only)
 - High-pass filter: 6 dB/oct., sweepable from Off to 1 kHz (main channels and aux's only)
- 4-band semi-parametric equalization
 - Low EQ: sweepable from 36 Hz to 465 Hz, ± 15 dB, switchable shelf or peaking
 - Low Mid EQ: sweepable from 90 Hz to 1.2 kHz, ± 15 dB, switchable 0.55/2.0 Q
 - High Mid EQ: sweepable from 380 Hz to 5 kHz, ± 15 dB, switchable 0.55/2.0 Q
 - High EQ: sweepable from 1.4 kHz to 18 kHz, ± 15 dB, switchable shelf or peaking
- Gate: Threshold 0 to -84 dB; Rate: 2 to 0.05 sec
- Compressor: Threshold -56 to 0 dB, Ratio 1:1 to 14:1, Attack 0.2 to 150 ms, Release 40 to 1000 ms, Makeup Gain 0 to 28 dB, Soft Knee switch, Auto Mode with 10 ms Attack and 150 ms Release
- Limiter: 0 dBFS Threshold, ∞ :1 Ratio
- Output Assign: 4 subgroups and main with post-EQ/post-dynamics option
- All settings can be copied among channels and saved as user presets.
- 50 channel-strip presets for drums, bass, guitars, keyboards, and vocals
- 2 internal digital effects-processors, each with 50 customizable reverb and delay presets
- 31-band graphic equalizers
 - Available on Main Outputs only
- Scene Store and Recall
- Global Scene Storage: all current StudioLive settings
 - Up to 80 at a time
- Automatic Global AutoStore
- Individual channel-strip Scene storage
 - Up to 48 at a time, plus...
 - 50 factory presets for instruments and vocal
- Copy and Paste between channels
- Customizable naming (for example, "Saturday Gig" or "Main Worship Service")
- Lockout mode to keep inspired amateurs from changing your settings

- Metering/Displays
 - 16 x 16- LED Fat Channel matrix:
 - Pre-dynamics/pre-fader input
 - Post-dynamics/post-fader output
 - Gain reduction
 - Aux 1-6 and EFX A/B output
 - Fader-position recall
 - 8 x 15-LED main meter bank
 - Selected channel level
 - Selected channel gain reduction
 - Sub buses 1 to 4
 - Main stereo outputs
 - 15-LED horizontal Pan/Balance display
 - 64 x 194 LCD matrix
 - Effects parameters
 - Scene creation, storage, and recall
 - System menus
 - 2-digit Channel Selected display
- Input/Output
 - 16 main inputs, each with XLR mic, 1/4" line, and 1/4" inserts
 - 2 1/4" stereo (L/R) aux inputs
 - 1 XLR talkback-mic input with phantom power and level control
 - Unbalanced RCA stereo (L/R) tape inputs and outputs
 - XLR stereo (L/R) main outputs with level control
 - 1/4" stereo (L/R) main outputs
 - XLR mono output with level control
 - 1/4" stereo (L/R) control-room outputs
 - 1/4" Headphone output
 - 4 1/4" subgroup outputs
 - 6 1/4" aux outputs
 - 16 pre-insert, balanced direct outputs, Ch. 1-8 and 9-16 (DB25 sockets)
 - S/PDIF digital out
 - 2 FireWire 400 ports
- Digitalia
 - High-definition analog-to-digital converters (118 dB dynamic range)
 - Unlimited-headroom, 32-bit floating point, digital mixing and effects processing
 - Internal sample frequency 44.1 kHz and 48 kHz
- Physical
 - Rugged, non-flex steel chassis
 - 100 mm long-throw faders
 - Military-grade, quick-touch buttons
 - BNC 12V lamp socket
 - Optional dust covers available
- Software bundle for Mac® and Windows® includes:
 - PreSonus Studio One® Artist digital audio workstation
 - PreSonus Capture™ live-recording software

- PreSonus Universal Control with Virtual StudioLive™ bidirectional mixer-control software
- Free downloadable software from the Apple App Store provides wireless remote control, including:
 - PreSonus StudioLive Remote for iPad®
 - PreSonus QMix™ for iPhone® and iPod touch®