marantz

PM6006



The PM6006 is an again upgraded successor of the multi-award-winning PM6005. Of course, we have retained the pre-amp and power-amp sections that exclusively feature discrete components - not a single IC in sight of the signal path. The PM6006 is upgraded for peak current at the amplifier stage, which makes it possible to refine the sound for you in much more detail. You can connect this superb integrated amplifier directly to a vast range of digital sources and use its superior 24bit/192kHz high current CS4398 DAC to create an unbelievably high level of audio enjoyment with new media. Furthermore, the unit includes now 2 optical and 1 coaxial digital inputs (an additional optical input from the predecessor, PM6005). And the complete digital section is fully shielded by an extra metal housing to ensure that the digital stage has no effect on the analogue signal. And of course all of the original features - such as five-line audio input including phono, two-pairs of gold-plated speaker connections with the convenience of bi-wiring, and a remote handset - are all still there. The lower impedance shielded Toroidal transformer, as well as customized components and unique Marantz HDAM modules care for powerful, dynamic and detailed original Marantz sound. In short, the new PM6006 is a new star with excellent genes.

Highlights	Your Benefits
Integrated Current Feedback Amplifier with 2x 45W / 8 ohm rms	Wide bandwith sound and enough power for medium size rooms
Further sound tuned with carefully selected components	Unique Marantz audio experience
Digital inputs (2x opt. / 1x coax.)	For extended connectivity and High Resolution Audio support (192kHz/24bit PCM)
High quality DAC CS4398 and Marantz HDAM SA2	Best sound quality from digital input signal
Fully shielded DAC unit; copper screws; rigid feet	Eliminating interferences for purity of sound
Gold Plated Inputs/Outputs incl. Phono (MM) input	Best connection for external sources
Marantz proprietary HDAM-SA3 circuits	Wider dynamic range with lower distortion for the output stage
Toroidal Transformer and high quality customized components	Delivering more power while causing less interferences
High quality Speaker Terminals (A / B switchable)	Improved connection to speakers
Available in black or silver-gold	Perfectly matching CD6006 CD Player and NA6005 Network Audio Player

www.marantz.eu

ecause music matters



PM6006 INTEGRATED AMPLIFIER WITH DIGITAL INPUT





PM6006

2 • • / • CS4398 SA3, SA2 • • • • • • • • •

• • •

5 2/• 1 •

4 •

•

100

45 W / 60 W

10 Hz - 70 kHz 0.08 %

MM 83 dB

MM 2.2 mV / 47 k0hm

High level 200 mV / 20 kOhm

High level 102dB (2V input)

Metal (Gold) Screw

FEATURES		
Channels		
Current Feedback Topology		
Phono EQ: Standard		
Digital in: optical / coaxial		
DAC chip		
HDAM version		
Toroidal Power Transformer		
High Grade Audio Components		
Customised Components		
Aluminium extrusion heat sink		
Balance / Bass / Treble / Loudness		
OTHERS		
Linear Drive Power Supply		
Shottky diodes		
Copper plated screws		
Source Direct		
Standby Mode		
INPUTS / OUTPUTS		
Audio Inputs		
Digital in: optical / coaxial		
Phono Input: MM		
Audio Outputs		
Gold Plated Cinch		
Speaker A / B		
Speaker Terminals:		
Number of terminals		
D-Bus		
Headphone Out		
Headphone Volume Control		
SPECIFICATIONS		
Power Output (8 / 4 Ohm RMS)		
Frequency Response		
Total Harmonic Distortion		
Damping Factor		

Available colors: Black / Silver-Gold		er-Gold	• / •
Metal	Front Panel		•
Power Consumption			155 W
Standby Consumption			0.3 W
Auto Power off			•
Detachable Power Cable			•
Remote Control			RC003PMCD
System Remote Function			•
Maximum Dimensions (W x D x H)			440 x 370 x 105 mm
Weight			7.6 kg
EAN			
EU	PM6006/N1B	4951035057810	Black
	PM6006/N1SG	4951035057827	Silver-Gold
UK	PM6006/T1B	4951035060063	Black
	PM6006/T1SG	4951035060070	Silver-Gold

Perfect partner

CD6006

GENERAL



CD Player

NA6005



Network Audio Player

Input Sensitivity

Signal to Noise Ratio Input Sensitivity

Signal to Noise Ratio