

Roland - MOBILE BA

Detailed Specifications

Rated Power Output: 2.5 W + 2.5 W

Nominal Input Level (1 kHz): MIC: -50 dBu LINE: -10 dBu PC/AUDIO: -10 dBu

Speakers: 10 cm (4 inches) x 2

Controls:

- POWER switch
- TONE knob
- MIC ECHO knob
- [MIC] VOLUME knob
- [LINE] VOLUME knob
- [PC/AUDIO]
- VOLUME knob
- CENTER CANCEL switch

Indicator: Power

Connectors:

- MIC jack (1/4-inch phone type)
- LINE L/MONO jack (1/4-inch phone type)
- LINE R jack (1/4-inch phone type)
- PC/AUDIO jacks (Stereo miniature phone type, RCA phono type)
- PHONES jack (Stereo miniature phone type) DC IN jack

Power Supply: Alkaline battery (AA, LR6) x 6 or AC Adaptor (sold separately)

Expected battery life under continuous use: Alkaline battery (AA, LR6): approximately 15 hours

*These figures will vary depending on the specifications of the batteries and the actual conditions of use.

Current Draw: 175 mA (DC 9 V)

Included Accessories:

- Strap Alkaline battery (AA, LR6) x 6
- Owner's Manual

Physical Specs:

- **Width:** 280 mm - 11-1/16 inches
- **Depth:** 108 mm - 4-5/16 inches
- **Height:** 177 mm - 7 inches
- **Weight:** 2.5 kg - 5 lbs. 9 oz.