

Casio Celviano AP-220 Digital Piano

Features/Specifications

- **Keyboard:** 88-key piano keyboard, with Touch Response (3 types)
- **Maximum:** Polyphony 128 notes
- **Tones:** 250 (with Layer and Split)
- **Effects:** Reverb (4 types), Chorus (4 types), Brilliance (3 to 0 to 3), Acoustic Resonance
- **Metronome:** Beats per measure: 0, 2, 3, 4, 5, 6, Tempo Range: 20 to 255
- **Duet:** Adjustable tone range: 0 to 3 octaves for the left keyboard; 4 to 1 octaves for the right keyboard
- **Auto Accompaniment:** Built-in Rhythms: 180, User Rhythms: Up to 10 (Approximately 40KB* maximum per rhythm), One Touch Presets: 180 types, Auto Harmonize: 12 types
- **Demo Songs:** 68 (8 tone demo songs; 60 Music Library songs)
- **Music Library:** Built-in Songs: 60, User Songs: Up to 10 (320KB* maximum per song)
- **Music Presets:** Built-in Presets: 300
- **User Presets:** Up to 50 (Approximately 8KB* maximum per preset)
- **Registration:** (4 rhythm areas + 8 tone areas) × 8 banks
- **Recorder:** Functions: Real-time recording, playback, Number of Songs: 5, Number of Tracks: 17 (System Track + Tracks 01 through 16), Capacity: Approximately 50,000 notes total (Up to approximately 10,000 notes per song), Punch-in recording
- **Pedals:** Damper (with half-pedal operation), Soft, Sostenuto
- **Other Functions:** Transpose: ±1 octave (12 to 00 to 12), Tuning: A4 = 440.0 Hz ±99 cents, Octave Shift: ±2 octaves, Temperaments: 17 types, Stretch Tune, Panel Lock
- **MIDI:** 16 multi-timbre received, GM Level 1 standard
- **SD Memory Card:** SD memory card slot, Supported SD Memory Cards: Up to 2GB, Functions: SMF playback, file storage, file recall, card format
- **Inputs/Outputs:** Phones jacks: Stereo standard jacks × 2, MIDI Out/In terminals, Line Out R, L/Mono jacks: Standard jacks × 2
- **Output impedance:** 2.8K
- **Output voltage:** 1.8V (RMS) MAX, Line In R, L/Mono jacks: Standard jacks × 2
- **Input impedance:** 9.0K
- **Input voltage:** 200mV, USB port: Type B, Pedal connector
- **Speakers:** 16cm × 2 + 5cm × 2 (Output 30W + 30W)
- **Power Requirements:** AP-620BK/AP-6BP: 120V AP-620BKV/AP-6BPV: 220-240V
- **Power Consumption:** 78W
- **Dimensions:** Digital Piano and Stand: 141.2 (W) × 49.2 (D) × 90.0 (H) cm
- **Weight:** Digital Piano and Stand: AP-620BK/AP-620BKV: Approximately 57.1 kg