



MultiMix16FX Technical Specifications

INPUTS:

- Channels 1-8 (mono):
- Mic: XLR with switchable phantom power
- Line: 1/4" Mono
- Insert: 1/4" TRS
- Low-cut (75 Hz) filter
- Gain Knob
- Guitar Direct (Channel 8)
- Channels 9-16 (stereo pairs):
- Line: 1/4" Left, Right
- 2-Track: RCA Left, Right
- Aux Return: 1/4" Left, Right

OUTPUTS:

- Main: 1/4" Left, Right
- Monitor: 1/4" Left, Right
- 2-Track: RCA Left, Right
- Aux Send: 1/4"
- FX Send: 1/4"
- Headphones: Stereo 1/4"

USB Audio:

- 2-Channel Audio In
- 2-Channel Audio Out
- 16-bit; 44.1/48 kHz